
EN
TW

Brook

UNIVERSAL FIGHTING BOARD

User Guide




The Universal Fighting Board features a low-latency design and supports various models, including XB Series X|S, XB 1, XB 360, PS5 for playing PS4 games, PS4, PS3, PC, Wii U, Switch, PS Mini, NeoGeo Mini, and MD mini. It's a multi-platform compatible universal fighting board.

Brook INSIDE

© Brook All Rights Reserved.
www.brookaccessory.com

How to connect the keys

EN
TW




J2 SOCD resolution mode selection

Mode 0: LR Cancel & Up Priority (Default)

Mode 1: Second-Input Priority (SIP)


EN

TW



Mode 0

Open circuit















Mode 1

Short circuit


J5 Player LED Guide

● LED ON ○ LED OFF

Player	PS4	PS3	XB 1	XB 360
1P				
2P				
3P				
4P				
5P	.....		.....	.....
6P	.....		.....	.....
7P	.....		.....	.....

EN
TW

J6 - 1 Detail




J8 Turbo function setting

Hold down the turbo button, then press the button for the function you want to set or cancel.

The following buttons can be set to the Turbo function：
1P、2P、3P、4P、1K、2K、3K、4K、L3、R3

J9 Detail




Console manual selection

The Brook UNIVERSAL FIGHTING BOARD PCB support manual selection of PS5,PS4, PS3, XB 1, XB 360 mode and Wii U / Switch, suggest be set to XB 360 mode on PC.

EN
TW

Manual Mode



Step.1 Press button.

1P ● = PS3
2P ● = PS4, PS5
3P ● = XB 360
4P ● = XB 1
1K ● = Wii U - Pokken Tournament
2K ● = XB Original
1P ● + 2P ● = PS Classic
1P ● + 1K ● = MD mini

Step.2 While Pressing connect fightstick to PC / Console

* When uses manual mode, the device mode will be saved automatically. If you want to switch back to the automatic detection mode, please hold down "Option (menu)" button and then plug USB cable to PC / console.

EN
TW

Brook

ZEROPLUS TECHNOLOGY CO.,LTD.

www.brookaccessory.com

Visit our website for more information and assistance.

©2023 Zeroplus Technology Co., Ltd. All Rights Reserved.
Brook is the registered trademark of Zeroplus Technology Co., Ltd. The other trademark names are the used marks, trademarks or registered trademarks of the corresponding companies.

Brook Gaming


202311V3

EN
TW

Brook

UNIVERSAL FIGHTING BOARD

使用者指南




Universal Fighting Board 擁有低延遲設計，並支援 XB Series X|S/ XB 1/ XB 360/ PS5 玩 PS4 遊戲 / PS4/ PS3/ PC/ Wii U/ Switch/ PS Mini/ NeoGeo Mini/ MD mini 多種型號，是一款多平台支援的萬能格鬥板。

Brook INSIDE

© Brook All Rights Reserved.
www.brookaccessory.com

如何連接

EN
TW



接地線
電源線
OPTIONS
START
SHARE
SELECT
BACK
HOME
PS
XB
4P/L1/LB
3P/R1/RB
2P/△/Y
1P/□/X
4K/L2/LT
3K/R2/RT
2K/O/B
1K/X/A
UP
RIGHT
LEFT
DOWN
J3
GND 4K 3K 2K 1K GND 4P 3P 2P 1P START SELECT PS/XBOX GND GND RIGHT LEFT UP DOWN VCC
J2
Brook
4 in 1
FIGHTING
www.brookaccessory.com
J6
J7
LS
DP
RS
J9
19
20
1
2
VCC P1 P2 P3 P4
J5
TPKEY L3 R3 GND
J4
G D+ D- V
J6-1
VCC TBLED TBKEY GND
J8
DP MODE
RS MODE
LS MODE
TURBO
KEY
TURBO
LED
PLAYER
LED
TOUCH PAD KEY
SELECT
BACK
L3/LSB
R3/RSB

J2 SOCD 方向衝突判定模式選擇

Mode 0: (默認) 方向左右衝突時，判定取消輸出。
方向上下衝突時，輸出方向為上。













Mode 1: 任意方向衝突時，輸出最後按下的按鈕方向。

EN
TW




J5 玩家燈號顯示指南

● LED ON ○ LED OFF

Player	PS4	PS3	XB 1	XB 360
1P				
2P				
3P				
4P				
5P	.....		.....	.....
6P	.....		.....	.....
7P	.....		.....	.....

EN
TW

J6 - 1 配線圖




J8 連發功能設定

按住連發設定鈕，然後按下您要設定或取消連發功能的按鈕。

以下按鈕可以設置 **Turbo** 功能：

1P、2P、3P、4P、1K、2K、3K、4K、L3、R3

J9 引腳名稱




手動選擇模式

可手動設定 PS5/PS3 / PS4 / XB 360 / XB 1 / Wii U / PS classic / MD mini，在 PC 上建議選用 XB 360 模式。

EN
TW

手動模式操作步驟



步驟 *1.* 按住不放。

1P ● = PS3	1K ● = Wii U - Pokken Tournament
2P ● = PS4, PS5	2K ● = XB Original
3P ● = XB 360	1P ● + 2P ● = PS Classic
4P ● = XB 1	1P ● + 1K ● = MD mini

步驟 *2.* 大搖桿連接 PC 或 主機。

* 手動設定模式後，會自動儲存所選模式。如要切換回自動偵測模式，請按住“Option (menu)”並重新插上 USB 連接電腦或遊戲主機。

EN
TW

Brook

ZEROPLUS TECHNOLOGY CO.,LTD.

www.brookaccessory.com

Brook Gaming

欲了解更多詳情，請訪問我們的官方網站

©2023 Zeroplus Technology Co., Ltd. All Rights Reserved.
Brook is the registered trademark of Zeroplus Technology Co., Ltd. The other trademark names are the used marks, trademarks or registered trademarks of the corresponding companies.

202311V3